



# ProBatt C NEW

Waterproof DC Input Battery to Battery Chargers

# STERLING POWER



## Waterproof DC Input Battery to Battery Charger

12v to 24v

24v to 12v

12v to 12v

24v to 24v

12v to 36v

24v to 36v

**Why wait to arrive at your destination to plug in your battery charger?** With the Sterling **ProBatt C** you can charge a 12V / 24V / 36V battery bank from another 12V / 24V battery. Installation could not be simpler, simply plug the device between two batteries (e.g. starter and auxiliary).

This on-board solution is able to provide a calculated 4 step charging profile to your batteries **without being plugged into shore power**. The **ProBatt C** fools the alternator into working at maximum potential. The surplus power (power left over after charging the primary battery) is converted into a higher voltage and is used to **charge your auxiliary battery bank faster (dependant on alternator, typically 5 times faster) than using just a standard alternator!**

As the **ProBatt C** does not connect to the alternator there are no ECU nor warranty issues as there is no voltage rise on the engine management system.

As the **ProBatt C** current limits you do not need to rate this product to the size of your charging source - for example, the 120A model can work with a 200A alternator without causing any damage. This allows for flexibility.



- Lithium Charging Profile
- Desulphation mode
- Waterproof IP68
- 120A rating



Temp sensor



Remote Control

### Battery to Battery Charger

DC Input	DC Output	Amps out	Size L x W x D	Weight	Part nos
12	12	60	145 x 110 x 120	3	BBW1260
12	12	120	170 x 130 x 125	3	BBW12120
12	12	180	190 x 190 x 130	4	BBW12180
12	24	30	145 x 110 x 120	3	BBW122460
12	36	20	145 x 110 x 120	3	BBW123660
12	48	15	145 x 110 x 120	3	BBW124860
Remote control			52mm diameter		BBRCN
<b>Pro Charge B (below)</b>					
12	24	30	230 x 135 x 65	4	BBW1212
12	36	20	230 x 135 x 65	4	BBW1224
12	48	15	230 x 135 x 65	4	BBW1236

### Principle Features:

- ✓ Quick and easy installation
- ✓ 4 stage battery charging
- ✓ Charges aux batteries while on the move
- ✓ Recovers batteries 5 times faster than alt.
- ✓ Can charge: GEL, AGM, lead, lithium, desulphation
- ✓ Some models are fully waterproof
- ✓ Battery type selectable
- ✓ Up to 5 times faster and 100% more charge
- ✓ Remote panel optional



## BASS ANGLER



Pro Charge B  
Waterproof IP 68

### Ideal applications:

- Gas starter battery to auxiliary (12V – 12V)
- Diesel starter battery to auxiliary (24V – 12V)
- Gas starter battery to bow thruster (12V–24V)
- Gas starter battery to trolling bank (12v-36V)

Visit the Sterling website for the latest products and news [www.sterling-power.com](http://www.sterling-power.com)